



### WARNING

**WARNING — THE INSTALLATION MUST BE CARRIED OUT BY A QUALIFIED ELECTRICIAN.**

1. LED Flush Mounts are suitable for using in damp locations
2. Please keep the LED Flush Mounts away from any corrosive substance, and please use dry cloth when you clean it
3. LED Flush Mounts can only be installed by a qualified electrician
4. Before installation or maintenance, please disconnect the power to prevent electric shock



### Application Notice

1. RISK OF SHOCK — House electric current can cause painful shock or serious injury unless handled properly. For your safety, always remember to:
  - A) Turn OFF the power supply at the fuse or circuit breaker box before you install the fixture
  - B) Double-check all connections to be sure that they are tight and correct
2. This fixture is designed for use in a circuit protected by a fuse or circuit breaker. It is also designed to be installed in accordance with local electrical codes. If you are unsure about your wiring, consult a qualified electrician or local electrical inspector, and check your local electrical code
3. RISK OF CUTS — some metal parts in the fixture may have sharp edges. To prevent cuts and scrapes, wear gloves when handling the parts
4. Account for small parts and destroy packing material, as these may be hazardous to children
5. The light source contained in this luminaire shall only be replaced by the manufacturer or his service agent or a similar qualified person
6. Terminal block and the suspending accessories are not included. Installation must be performed by a qualified person

### CAUTION

**PLEASE READ INSTRUCTION BEFORE COMMENCING INSTALLATION AND RETAIN FOR FUTURE REFERENCES. Electrical products can cause death or injury, or damage to property.**

**If in any doubt about the installation or use of this product, consult a competent electrician.**

### INSTALLATION GUIDE

#### Tools Required



#### OPTION1: FLUSH MOUNT

**Fig. 1**

1. Pull the supply wires and house ground wire from the Outlet Box. Position the mounting plate over the Junction Box. Mark the location of the two holes located on the Mounting Plate. Be sure to mark only the narrow parts of the hole. Remove the Plate from the ceiling. Drill the two holes using the appropriate type and size drill bit. Insert anchors into the holes. (See Fig.1)

**Fig. 2**

2. Wire Connections : Connect the house ground wire to the fixture ground wire; connect the white supply wire to the white fixture wire; connect the black supply wire to the black fixture wire by using the wire connectors. Carefully tuck all wires back into the Junction Box. Adjust the 5CCT switch ( See Fig.2.)

**Fig. 3**

3. Snap and fix the clip in the bracket. ( See Fig. 3)

**Fig. 4**

4. Turn on the power and Light up the lamp. ( See Fig. 4 )

#### OPTION2: RETROFIT A RECESSED CAN

**Fig. 1**

1. Choose a 5-inch or 6-inch housing and secure it with screws at the corresponding holes on the bracket.

**Fig. 2**

2. Insert wires into Quick connector. Black to black and white to white. Attach ground Wire to ground screw in recessed can.

**Fig. 3**

3. Turn E26 lamp holder into socket base. Connect Quick Connectors Tuck all wires into recessed can. Squeeze springs and push up into recessed can.

**Fig. 4**

4. Turn on the power and Light up the lamp. ( See Fig. 4 )