

LED Emergency Lights

MODEL OE-212BP

ORTECH

Product Specification Sheet



HIGHLIGHTS

- LED Dual Head Emergency Light with battery pack backup and high efficiency LED remote heads
- Has 2 pieces 2W ultra bright LED lamp heads for emergency mode and 120V/277V/347V AC triple voltage operation
- Universal mounting pattern and key hole slots are stamped on the back and conduit knockouts on the sides of each unit
- Comes with built-in 6V 7Ah Lead-Acid battery for minimum 2 hours emergency operation
- Made of steel housing with lightweight thermal plastic head in matching colour, and has UL94V-0 flame rating
- Full recharge time is maximum 24 hours and is suitable for +10°C to +40°C indoor damp locations
- Provides overcharge & over-discharge protection
- Includes test switch and charge indicator
- Fast and Easy installation in minutes
- More than 200 lmn

SPECIFICATIONS

Model	OE-212BP
Wattage	36W Max.
Voltage	120V AC or 277V AC or 347V AC /60Hz
AC Charging Current	100mA AC Max.
DC Charging Voltage	5.25-7.5V DC
DC Charging Current	560mA DC Max.
Lumens	260 lmn
Material	Steel housing and light weight thermal plastic heads in matching colour
Battery	6V 7Ah
Battery Type	Lead-Acid Battery
Emergency Duration Time	≥ 120 min
Discharge Current	0.67-6.67A
Charging Time	≥ 120 min
Colour Temp.	6500K (Cool White)
Operating Temp.	+10°C ~ +40°C
Warranty	5 years

